

FSP040-DGAA1 of POP-70-G5 Power Electronics Test Report

Summary	<input checked="" type="checkbox"/> Pass <input type="checkbox"/> Fail <input type="checkbox"/> Pass with Deviation Comment: _____			
Test Result Summary				
	Critical	Major	Minor	Enhancement
Defect Found	0	0	0	0
Defect Unsolved	0	0	0	0

Issue date	Approval	Test Engineer
01/05/2012	Jansin Lee	Sean Hsu

Table of Contents

1. Project.....	3
2. Power Manufacturer	3
3. Team Member	3
4. Test Equipments	3
5. AC Adapter Spec.....	3
6. Test Item.....	4
6.1. AC Input Current.....	4
6.2. MAX Inrush Current	4
6.3. Input Frequency & Voltage	4
6.4. Switching Test.....	4
6.5. Efficiency.....	4
6.6. Line Regulation.....	4
6.7. Load Regulation	4
6.8. Over-Voltage Protection	4
6.9. Over-Circuit Protection	4
6.10. Over-Load Protection	4
6.11. Short Circuit Protect.....	4
6.12. Line Voltage Surge.....	4
6.13. Line Voltage Sag	5
6.14. Ripple & Noise	5
6.15. Setup Time	5
6.16. Hold up Time.....	5
6.17. Rise Time.....	5
6.18. Turn on Overshoot	5
6.19. Turn off Undershoot.....	5
6.20. Remote ON/OFF	5
6.21. Power Good Signal.....	5
6.22. Power On In Low Temperature	5
6.23. Power On In High Temperature	5
6.24. Room Burn-in test	5
6.25. On/Off Cycling	5
6.26. Power Consumption Test With DC Power	5
6.27. Adapter Power Consumption Test.....	5

1. Project

FSP040-DGAA1AC-DC Power for POP-70-G5

2. Power Manufacturer

FSP GROUP INC.

3. Team Member

PM : LEE LEE ; H/W : Peter Yao

4. Test Equipments

- 4.1. CPU Board : GENE-9455 B1.0 BIOS R.0.2 P7G5AA02 (11/30/2011)
- 4.2. Memory : DSL DDR2-667 2GB
- 4.3. HDD : Toshiba MK1060GSC 100GB
- 4.4. AC Adapter : FSP040-DGAA1 O/P: 12V/3.33A
- 4.5. USB Mouse : Logitech , Model : M-BT85
- 4.6. USB Keyboard : Logitech , Model : Y-BL49

5. AC Adapter Spec

AC Input : 100VAC~240VAC / 47Hz~63Hz

DC Output : 12Vdc Min Load : 0A Full Load : 3.33A / 40W

6. Test Item

Test Item	Test Condition / Specification		Measured	Result
6.1. AC Input Current	I/P:90VAC	1.3A	0.85A	PASS
6.2. MAX Inrush Current	I/P:115VAC	A	9.70A	-
	I/P:230VAC	A	9.85A	-
6.3. Input Frequency & Voltage	I/P:90VAC/47HZ	■ON □ OFF	-	PASS
	I/P:90VAC/63HZ	■ON □ OFF	-	PASS
	I/P:264VAC/47HZ	■ON □ OFF	-	PASS
	I/P:264VAC/63HZ	■ON □ OFF	-	PASS
6.4. Switching Test	Switching Time: 0.5 Sec MIN Load / Full Load	@90VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@115VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@230VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@264VAC ■ON □ OFF	-	PASS
6.5. Efficiency	I/P:115VAC FULL LOAD	@82%Min	83.650%	PASS
	I/P:230VAC FULL LOAD	@82%Min	84.480%	PASS
6.6. Line Regulation	I/P:90VAC~264VAC	<±%	0.026%	-
6.7. Load Regulation	I/P:115VAC O/P:MINLOAD~FULL LOAD	<±%	2.25%	-
	I/P:230VAC O/P:MINLOAD~FULL LOAD	<±%	2.26%	-
6.8. Over-Voltage Protection	I/P:230VAC O/P:MIN LOAD	V1 : 22V(MAX)	-	-
6.9. Over-Circuit Protection	O/P: 12V	5.5A(MAX)	4.36A	PASS
6.10. Over-Load Protection	I/P:90VAC O/P:MIN LOAD	165%	129.8%	PASS
	I/P:115VAC O/P:MIN LOAD	165%	129.7%	PASS
	I/P:230VAC O/P:MIN LOAD	165%	128.6%	PASS
	I/P:264VAC O/P:MIN LOAD	165%	130%	PASS
6.11. Short Circuit Protect	I/P:115VAC O/P:MIN LOAD	12V&GND Short	-	PASS
	I/P:230VAC O/P:MIN LOAD	12V&GND Short	-	PASS
6.12. Line Voltage Surge	O/P: FULL LOAD	Surge voltage from 132VAC to 147VAC (0.5sec), back to 132VAC	-	PASS
	O/P: FULL LOAD	Surge voltage from 264VAC to 293VAC (0.5sec), back to 264VAC	-	PASS

FSP040-DGAA1AC of POP-70-G5 Power Electronics Test Report

6.13. Line Voltage Sag	O/P: FULL LOAD	Sag voltage from 108VAC to 80VAC (0.5sec), back to 108VAC	-	PASS
	O/P: FULL LOAD	Sag voltage from 198VAC to 161VAC (0.5sec), back to 198VAC	-	PASS
6.14. Ripple & Noise	I/P:115VAC O/P:FULL LOAD	≤ 120mv	117.5 mv	PASS
	I/P:230VAC O/P:FULL LOAD	≤ 120mv	116mv	PASS
6.15. Setup Time	I/P:115VAC O/P:FULL LOAD	4S(MAX)	1.328S	PASS
	I/P:230VAC O/P:FULL LOAD	S(MAX)	86.3mS	-
6.16. Hold up Time	I/P:115VAC O/P:FULL LOAD	5mS(MIN)	12.6mS	PASS
	I/P:230VAC O/P:FULL LOAD	mS(MIN)	86.3mS	-
6.17. Rise Time	I/P:115VAC O/P:FULL LOAD	mS(MAX)	8.8mS	-
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	6.8mS	-
6.18. Turn on Overshoot	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
6.19. Turn off Undershoot	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
6.20. Remote ON/OFF	Simulate TTL signal to test this function			-
6.21. Power Good Signal	Shall go high level with a delay of100~500ms		-	-
6.22. Power On In Low Temperature	I/P:115VAC (0℃) After 2HR Power On			-
6.23. Power On In High Temperature	I/P:115VAC (50℃)After 2HR Power On			-
6.24. Room Burn-in test	I/P:115VAC O/P: FULL LOAD TA:25℃ BURN-IN DURATION : 2 hour			-
6.25. On/Off Cycling	Times / on: 20 sec / off: 10 sec			-
6.26. Power Consumption Test With DC Power	No Run Prime95	I/P:9VDC 1.22A 10.98W		PASS
	Run Prime95	I/P:9VDC 1.69A 15.21W		PASS
	No Run Prime95	I/P:30VDC 0.45A 13.5W		PASS
	Run Prime95	I/P:30VDC 0.51A 15.3W		PASS
6.27. Adapter Power Consumption Test	No Run Prime95	I/P:100VAC 0.32A 114.2W	O/P: 12V/0.98A	PASS
	Run Prime95	I/P:100VAC 0.39.A 17.8W	O/P: 12V1.25A	PASS