

Report NO: 14P0A0009\_I

# FSP060-DBAB1

## with

# ACD-110DHTT-A1-1010

## Power Electronics Test Report

Summary	<input checked="" type="checkbox"/> <b>Pass</b> <input type="checkbox"/> <b>Fail</b> <input type="checkbox"/> <b>Pass with Deviation</b> <b>Comment:</b> _____			
<b>Test Result Summary</b>				
	Critical	Major	Minor	Enhancement
Defect Found	0	0	0	0
Defect Unsolved	0	0	0	0

Issue date <hr style="width: 80%; margin: 0 auto;"/> <b>10/20/2014</b>	Approval <hr style="width: 80%; margin: 0 auto;"/> <b>Tom Lin</b>	Test Engineer <hr style="width: 80%; margin: 0 auto;"/> <b>Sean Hsu</b>
---	--	--

## Table of Contents

1.	Project.....	3
2.	Power Manufacturer .....	3
3.	Team Member .....	3
4.	Test Equipment .....	3
5.	AC Adapter Spec.....	3
6.	Test Item.....	4
	6.1. AC Input Current.....	4
	6.2. MAX Inrush Current .....	4
	6.3. Input Frequency & Voltage .....	4
	6.4. Switching Test.....	4
	6.5. Efficiency .....	4
	6.6. Line Regulation.....	4
	6.7. Load Regulation .....	4
	6.8. Over-Voltage Protection .....	4
	6.9. Over-Circuit Protection .....	4
	6.10. Over-Load Protection .....	4
	6.11. Short Circuit Protect.....	4
	6.12. Line Voltage Surge.....	4
	6.13. Line Voltage Sag .....	5
	6.14. Ripple & Noise.....	5
	6.15. Setup Time .....	5
	6.16. Hold up Time.....	5
	6.17. Rise Time.....	5
	6.18. Turn on Overshoot .....	5
	6.19. Turn off Undershoot .....	5
	6.20. Power On In Low Temperature .....	5
	6.21. Power On In High Temperature .....	5
	6.22. System Power Consumption Test .....	5

**1. Project**

FSP060-DBAB1 AC-DC Adapter for ACD-110DHTT-A1-1010

**2. Power Manufacturer**

FSP

**3. Team Member**

PM : Kim Lin : PPC H/W : Jack Peng

**4. Test Equipment**

4.1. ACD-110D : 10.1", WXGA, 1280x800, 250 nit, LED backlight

4.2. AC Adapter : FSP , Model : FSP060-DBAB1 , O/P : 12V/5A , 60Watt

4.3. USB Mouse : Logitech , Model : M-BT85

4.4. USB Keyboard : Logitech , Model : Y-BL49

**5. AC Adapter Spec**

AC Input : 100VAC~240VAC / 47Hz~63Hz

DC Output : 12Vdc Min Load : 0A Full Load : 5A / 60W

## 6. Test Item

Test Item	Test Condition / Specification		Sanction	
			Measured	Result
6.1. AC Input Current	I/P:115VAC	1.7A	1.18A	PASS
6.2. MAX Inrush Current	I/P:115VAC	A	8.55A	-
	I/P:230VAC	A	9.70A	-
6.3. Input Frequency & Voltage	I/P:90VAC/47HZ	■ON □ OFF	-	PASS
	I/P:90VAC/63HZ	■ON □ OFF	-	PASS
	I/P:264VAC/47HZ	■ON □ OFF	-	PASS
	I/P:264VAC/63HZ	■ON □ OFF	-	PASS
6.4. Switching Test	Switching Time: 0.5 Sec MIN Load / Full Load	@90VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@115VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@230VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@264VAC ■ON □ OFF	-	PASS
6.5. Efficiency	I/P:90VAC O/P:5A	@%Min	84.5%	-
	I/P:115VAC O/P:5A	@85%Min	85.158%	PASS
	I/P:230VAC O/P:5A	@85%Min	86.72%	PASS
	I/P:264VAC O/P:5A	@%Min	86.6%	-
6.6. Line Regulation	I/P:90VAC~264VAC	<±1%	0.28%	PASS
6.7. Load Regulation	I/P:115VAC O/P:MIN~FULL LOAD	<±5%	4.25%	PASS
	I/P:230VAC O/P:MIN~FULL LOAD	<±5%	4.05%	PASS
6.8. Over-Voltage Protection	I/P:230VAC O/P:MIN LOAD	V1 : 13~18 (MAX)	-	-
6.9. Over-Current Protection	O/P: 12V	7.2A(MAX)	7A	PASS
6.10. Over-Load Protection	I/P:90VAC O/P:MIN LOAD	144%	140%	PASS
	I/P:115VAC O/P:MIN LOAD	144%	138%	PASS
	I/P:230VAC O/P:MIN LOAD	144%	140%	PASS
	I/P:264VAC O/P:MIN LOAD	144%	139%	PASS
6.11. Short Circuit Protect	I/P:115VAC O/P:MIN LOAD	12V&GND Short	-	PASS
	I/P:230VAC O/P:MIN LOAD	12V&GND Short	-	PASS
6.12. Line Voltage Surge	O/P: FULL LOAD	Surge voltage from 132VAC to 147VAC (0.5sec), back to 132VAC	-	PASS
	O/P: FULL LOAD	Surge voltage from 264VAC to 293VAC (0.5sec), back to 264VAC	-	PASS

<b>6.13. Line Voltage Sag</b>	O/P: FULL LOAD	Sag voltage from 108VAC to 80VAC (0.5sec), back to 108VAC	-	PASS
	O/P: FULL LOAD	Sag voltage from 198VAC to 161VAC (0.5sec), back to 198VAC	-	PASS
<b>6.14. Ripple &amp; Noise</b>	I/P:115VAC O/P:FULL LOAD	$\leq 150\text{mv}$	97mv	PASS
	I/P:230VAC O/P:FULL LOAD	$\leq 150\text{mv}$	92mv	PASS
<b>6.15. Setup Time</b>	I/P:115VAC O/P:FULL LOAD	4S(MAX)	870ms	PASS
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	862ms	-
<b>6.16. Hold up Time</b>	I/P:115VAC O/P:FULL LOAD	8mS(MIN)	19.8ms	PASS
	I/P:230VAC O/P:FULL LOAD	8mS(MIN)	81.5ms	PASS
<b>6.17. Rise Time</b>	I/P:115VAC O/P:FULL LOAD	mS(MAX)	24.6ms	-
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	24.8ms	-
<b>6.18. Turn on Overshoot</b>	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
<b>6.19. Turn off Undershoot</b>	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
<b>6.20. Power On In Low Temperature</b>	I/P:115VAC ( 0°C ) After 2HR Power On			-
<b>6.21. Power On In High Temperature</b>	I/P:115VAC ( 50°C )After 2HR Power On			-
<b>6.22. System Power Consumption Test</b>	No Run Video	I/P:100VAC 0.09A 3.7W	O/P: 12V/0.26A 3.12W	PASS
	Run Video	I/P:100VAC 0.09A 4W	O/P: 12V/0.29A 3.48W	PASS