

FSP060-DBAB1 of ACD-518R-HTT-A2-1010 Power Electronics Test Report

Summary	<input checked="" type="checkbox"/> Pass <input type="checkbox"/> Fail <input type="checkbox"/> Pass with Deviation Comment: _____			
Test Result Summary				
	Critical	Major	Minor	Enhancement
Defect Found	0	0	0	0
Defect Unsolved	0	0	0	0

Issue date	Approval	Test Engineer
12/09/2011	Jansin Lee	Sean Hsu

Table of Contents

1. Project.....	3
2. Power Manufacturer	3
3. Team Member	3
4. Test Equipment	3
5. AC Adapter Spec.....	3
6. Test Item.....	4
6.1. AC Input Current.....	4
6.2. MAX Inrush Current	4
6.3. Input Frequency & Voltage	4
6.4. Switching Test.....	4
6.5. Efficiency.....	4
6.6. Line Regulation.....	4
6.7. Load Regulation	4
6.8. Over-Voltage Protection	4
6.9. Over-Circuit Protection	4
6.10. Over-Load Protection	4
6.11. Short Circuit Protect.....	4
6.12. Line Voltage Surge.....	4
6.13. Line Voltage Sag	5
6.14. Ripple & Noise	5
6.15. Setup Time	5
6.16. Hold up Time.....	5
6.17. Rise Time.....	5
6.18. Turn on Overshoot	5
6.19. Turn off Undershoot	5
6.20. Power On In Low Temperature	5
6.21. Power On In High Temperature	5
6.22. System Power Consumption Test	5

1. Project

FSP060-DBAB1 AC-DC Adapter for ACD-518R-HTT-A2-1010

2. Power Manufacturer

FSP

3. Team Member

PM : LEE LEE ; PPC H/W : Peter Yao

4. Test Equipment

4.1. ACD-518R : 18.5" Infotainment Multi-Touch Display

4.2. ACG-204-A2 : Gateway

4.3. AC Adapter : FSP , Model : FSP060-DBAB1 , O/P : 12V/5A , 60Watt

4.4. USB Mouse : Logitech , Model : M-BT85

4.5. USB Keyboard : Logitech , Model : Y-BL49

5. AC Adapter Spec

AC Input : 100VAC~240VAC / 47Hz~63Hz

DC Output : 12Vdc Min Load : 0A Full Load : 5A / 60W

FSP060-DBAB1 of ACD-518R-HTT-A2-1010 Power Electronics Test Report

6. Test Item

Test Item	Test Condition / Specification		Sanction	
			Measured	Result
6.1. AC Input Current	I/P:115VAC	1.7A	1.17A	PASS
6.2. MAX Inrush Current	I/P:115VAC	A	8.52A	-
	I/P:230VAC	A	9.68A	-
6.3. Input Frequency & Voltage	I/P:90VAC/47HZ	■ON □ OFF	-	PASS
	I/P:90VAC/63HZ	■ON □ OFF	-	PASS
	I/P:264VAC/47HZ	■ON □ OFF	-	PASS
	I/P:264VAC/63HZ	■ON □ OFF	-	PASS
6.4. Switching Test	Switching Time: 0.5 Sec MIN Load / Full Load	@90VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@115VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@230VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@264VAC ■ON □ OFF	-	PASS
6.5. Efficiency	I/P:90VAC O/P:5A	@%Min	84.488%	-
	I/P:115VAC O/P:5A	@85%Min	85.157%	PASS
	I/P:230VAC O/P:5A	@85%Min	86.70%	PASS
	I/P:264VAC O/P:5A	@%Min	86.56%	-
6.6. Line Regulation	I/P:90VAC~264VAC	<±1%	0.26%	PASS
6.7. Load Regulation	I/P:115VAC O/P:MIN~FULL LOAD	<±5%	4.21%	PASS
	I/P:230VAC O/P:MIN~FULL LOAD	<±5%	4.05%	PASS
6.8. Over-Voltage Protection	I/P:230VAC O/P:MIN LOAD	V1 : 13~18 (MAX)	-	-
6.9. Over-Circuit Protection	O/P: 12V	7.2A(MAX)	7A	PASS
6.10. Over-Load Protection	I/P:90VAC O/P:MIN LOAD	144%	140%	PASS
	I/P:115VAC O/P:MIN LOAD	144%	138%	PASS
	I/P:230VAC O/P:MIN LOAD	144%	140%	PASS
	I/P:264VAC O/P:MIN LOAD	144%	139%	PASS
6.11. Short Circuit Protect	I/P:115VAC O/P:MIN LOAD	12V&GND Short	-	PASS
	I/P:230VAC O/P:MIN LOAD	12V&GND Short	-	PASS
6.12. Line Voltage Surge	O/P: FULL LOAD	Surge voltage from 132VAC to 147VAC (0.5sec), back to 132VAC	-	PASS
	O/P: FULL LOAD	Surge voltage from 264VAC to 293VAC (0.5sec), back to 264VAC	-	PASS

FSP060-DBAB1 of ACD-518R-HTT-A2-1010 Power Electronics Test Report

6.13. Line Voltage Sag	O/P: FULL LOAD	Sag voltage from 108VAC to 80VAC (0.5sec), back to 108VAC	-	PASS
	O/P: FULL LOAD	Sag voltage from 198VAC to 161VAC (0.5sec), back to 198VAC	-	PASS
6.14. Ripple & Noise	I/P:115VAC O/P:FULL LOAD	$\leq 150\text{mv}$	96mv	PASS
	I/P:230VAC O/P:FULL LOAD	$\leq 150\text{mv}$	90mv	PASS
6.15. Setup Time	I/P:115VAC O/P:FULL LOAD	4S(MAX)	886ms	PASS
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	868ms	-
6.16. Hold up Time	I/P:115VAC O/P:FULL LOAD	8mS(MIN)	19.5ms	PASS
	I/P:230VAC O/P:FULL LOAD	8mS(MIN)	81.2ms	PASS
6.17. Rise Time	I/P:115VAC O/P:FULL LOAD	mS(MAX)	24.5ms	-
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	24.8ms	-
6.18. Turn on Overshoot	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
6.19. Turn off Undershoot	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
6.20. Power On In Low Temperature	I/P:115VAC (0°C) After 2HR Power On			-
6.21. Power On In High Temperature	I/P:115VAC (50 °C)After 2HR Power On			-
6.22. System Power Consumption Test	No Run Video	I/P:100VAC 0.21A 8.6W	ACG-204 O/P: 12V/0.66A	PASS
	Run Video	I/P:100VAC 0.21A 9W	ACG-204 O/P: 12V/0.7A	PASS
	No Run Video	I/P:100VAC 0.77A 34.1W	ACD-518R O/P: 12V/2.3A	PASS
	Run Video	I/P:100VAC 0.78A 34.9W	ACD-518R O/P: 12V/2.32A	PASS