

Report NO: 14P0A0002_I

FSP060-DBAE1 of ACP-1073 Power Electronics Test Report

Summary	<input type="checkbox"/> Pass			
	<input type="checkbox"/> Fail			
	<input checked="" type="checkbox"/> Pass with Deviation			
	Comment: Measured Efficiency not meet Power Supply product spec			
Test Result Summary				
	Critical	Major	Minor	Enhancement
Defect Found	0	0	0	0
Defect Unsolved	0	0	0	0

Issue date

01/29/2014

Approval

Tom Lin

Test Engineer

Sean Hsu

Table of Contents

1. Project.....	3
2. Power Manufacturer	3
3. Team Member	3
3. Test Equipment.....	3
5. AC Adapter Spec.....	3
6. Test Item.....	4
6.1. AC Input Current.....	4
6.2. MAX Inrush Current	4
6.3. Input Frequency & Voltage	4
6.4. Switching Test.....	4
6.5. Efficiency	4
6.6. Line Regulation.....	4
6.7. Load Regulation	4
6.8. Over-Voltage Protection	4
6.9. Over-Circuit Protection	4
6.10. Over-Load Protection	4
6.11. Short Circuit Protect.....	4
6.12. Line Voltage Surge.....	5
6.13. Line Voltage Sag	5
6.14. Ripple & Noise.....	5
6.15. Setup Time	5
6.16. Hold up Time.....	5
6.17. Rise Time.....	5
6.18. Turn on Overshoot	5
6.19. Turn off Undershoot	5
6.20. Remote ON/OFF	5
6.21. Power Good Signal.....	5
6.22. Power On In Low Temperature	5
6.23. Power On In High Temperature	5
6.24. System Power Consumption Test	5

1. Project

FSP060-DBAE1 AC-DC Adapter for ACP-1073

2. Power Manufacturer

FSP

3. Team Member

PM : Alan Chou ; H/W : Peter Yao

3. Test Equipment

4.1. CPU Board : AAEON , PBA-CV02 , Rev : A1.0 BIOS : R1.1(1073AM11) (11/21/2013)

4.2. CPU : INTEL , ATOM N2600 1.6GHz

4.3. mSATA : Memoright , 16GB , M/N : MSM-500

4.4. Memory : SEC , 2GB , M/N : K4B2G0846D

4.5. Power Supply : FSP , M/N : FSP060-DBAE1 , O/P : 60Watt

4.6. USB Mouse : Logitech , Model : M-BT85

4.7. USB Keyboard : Logitech , Model : Y-BL49

5. AC Adapter Spec

AC Input : 100VAC~240VAC / 47Hz~63Hz

DC Output : 12Vdc Min Load : 0A Full Load : 5A / 60W

6. Test Item

Test Item	Test Condition / Specification		Sanction	
			Measured	Result
6.1. AC Input Current	I/P:90VAC	1.5A	1.38A	PASS
6.2. MAX Inrush Current	I/P:115VAC	A	8.55A	-
	I/P:230VAC	A	9.56A	-
6.3. Input Frequency & Voltage	I/P:90VAC/47HZ	■ON □ OFF	-	PASS
	I/P:90VAC/63HZ	■ON □ OFF	-	PASS
	I/P:264VAC/47HZ	■ON □ OFF	-	PASS
	I/P:264VAC/63HZ	■ON □ OFF	-	PASS
6.4. Switching Test	Switching Time: 0.5 Sec MIN Load / Full Load	@90VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@115VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@230VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@264VAC ■ON □ OFF	-	PASS
6.5. Efficiency	I/P:90VAC O/P:5A	@%Min	84.244%	-
	I/P:115VAC O/P:5A	@87%Min	85.453%	Fail
	I/P:230VAC O/P:5A	@87%Min	86.113%	Fail
	I/P:264VAC O/P:5A	@%Min	86.002%	-
6.6. Line Regulation	I/P:90VAC~264VAC	<±3%	0.4%	PASS
6.7. Load Regulation	I/P:115VAC O/P:MIN~FULL LOAD	<±5%	4.375%	PASS
	I/P:230VAC O/P:MIN~FULL LOAD	<±5%	4.483%	PASS
6.8. Over-Voltage Protection	I/P:230VAC O/P:MIN LOAD	V1 : 13~18 (MAX)	-	-
6.9. Over-Circuit Protection	O/P: 12V	2A(MAX)	6.72A	PASS
6.10. Over-Load Protection	I/P:90VAC O/P:MIN LOAD	200%	124%	PASS
	I/P:115VAC O/P:MIN LOAD	200%	134.4%	PASS
	I/P:230VAC O/P:MIN LOAD	200%	138.4%	PASS
	I/P:264VAC O/P:MIN LOAD	200%	138%	PASS
6.11. Short Circuit Protect	I/P:115VAC O/P:MIN LOAD	12V&GND Short	-	PASS
	I/P:230VAC O/P:MIN LOAD	12V&GND Short	-	PASS

6.12. Line Voltage Surge	O/P: FULL LOAD	Surge voltage from 132VAC to 147VAC (0.5sec), back to 132VAC	-	PASS
	O/P: FULL LOAD	Surge voltage from 264VAC to 293VAC (0.5sec), back to 264VAC	-	PASS
6.13. Line Voltage Sag	O/P: FULL LOAD	Sag voltage from 108VAC to 80VAC (0.5sec), back to 108VAC	-	PASS
	O/P: FULL LOAD	Sag voltage from 198VAC to 161VAC (0.5sec), back to 198VAC	-	PASS
6.14. Ripple & Noise	I/P:115VAC O/P:FULL LOAD	$\leq 150\text{mv}$	93.8mv	PASS
	I/P:230VAC O/P:FULL LOAD	$\leq 150\text{mv}$	89.1mv	PASS
6.15. Setup Time	I/P:90VAC O/P:FULL LOAD	3S(MAX)	1.27ms	PASS
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	670ms	-
6.16. Hold up Time	I/P:115VAC O/P:FULL LOAD	8mS(MIN)	22ms	PASS
	I/P:230VAC O/P:FULL LOAD	20mS(MIN)	52.4ms	PASS
6.17. Rise Time	I/P:115VAC O/P:FULL LOAD	40mS(MAX)	14.1ms	PASS
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	11.2ms	-
6.18. Turn on Overshoot	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
6.19. Turn off Undershoot	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
6.20. Remote ON/OFF	Simulate TTL signal to test this function			-
6.21. Power Good Signal	Shall go high level with a delay of 100~500ms			-
6.22. Power On In Low Temperature	I/P:115VAC (0°C) After 2HR Power On			-
6.23. Power On In High Temperature	I/P:115VAC (°C)After 2HR Power On			-
6.24. System Power Consumption Test	Off Mode	I/P:100VAC	I/P:1.8W	PASS
	Sleep Mode	I/P:100VAC	I/P:1.6W	PASS
	Idle Mode No Run Prime95	I/P:100VAC 0.26A 12.7W	O/P: 12V/0.7A 8.4W	PASS
	Idle Mode Run Prime95	I/P:100VAC 0.3A 14.7W	O/P: 12V/0.95A 11.4W	PASS