

Report No: 15P0A0014\_I

# FSP060-DIBAN2

## with

# ACP-1074

## Power Electronics Test Report

Summary	<input checked="" type="checkbox"/> Pass			
	<input type="checkbox"/> Fail			
<input type="checkbox"/> Pass with Deviation				
Comment:				
Test Result Summary				
	Critical	Major	Minor	Enhancement
Defect Found	0	0	0	0
Defect Unsolved	0	0	0	0

Issue date	Approval	Test Engineer
<b>11/20/2015</b>	<b>KJ Wang</b>	<b>Mike Lee</b>

## Table of Contents

1. Project.....	3
2. Power Manufacturer .....	3
3. Team Member .....	3
4. Test Equipment.....	3
5. AC Adapter Spec.....	3
6. Test Item.....	4
6.1. AC Input Current.....	4
6.2. MAX Inrush Current .....	4
6.3. Input Frequency & Voltage .....	4
6.4. Switching Test.....	4
6.5. Efficiency .....	4
6.6. Line Regulation.....	4
6.7. Load Regulation .....	4
6.8. Over-Voltage Protection .....	4
6.9. Over-Current Protection .....	4
6.10. Over-Load Protection .....	4
6.11. Short Circuit Protect.....	4
6.12. Line Voltage Surge.....	5
6.13. Line Voltage Sag .....	5
6.14. Ripple & Noise.....	5
6.15. Setup Time .....	5
6.16. Hold up Time.....	5
6.17. Rise Time.....	5
6.18. Turn on Overshoot .....	5
6.19. Turn off Undershoot.....	5
6.20. Remote ON/OFF .....	5
6.21. Power Good Signal.....	5
6.22. Power Consumption Test with AC Adapter .....	5

**1. Project**

FSP060-DIBAN2 AC-DC Adapter for ACP-1074

**2. Power Manufacturer**

FSP

**3. Team Member**

PM : Tim Lin ; H/W : Peter Yao

**4. Test Equipment**

4.1. LCD Monitor : ASUS , Model : PA238

4.2. PCB Board : PBA-BT01 Rev.1.00

4.3. CPU : Intel® Celeron® Processor J1900 @ 1.9GHz

4.4. M-SATA : innodisk m-sata 3ME3 32GB

4.5. Memory : Transcend DDR3L 1600 2GB (TS256MSK64W6N-AA SEC K4B2G0846Q)

**5. AC Adapter Spec**

AC Input : 90VAC~264VAC / 47Hz~63Hz

DC Output : 12VDC Min Load : 0A Full Load : 5A / 60W

## 6. Test Item

Test Item	Test Condition / Specification		Sanction	
			Measured	Result
6.1. AC Input Current	I/P:90VAC	1.5A	1.31A	PASS
6.2. MAX Inrush Current	I/P:115VAC	A	A	-
	I/P:230VAC	A	A	-
6.3. Input Frequency & Voltage	I/P:90VAC/47HZ	■ON □ OFF	-	PASS
	I/P:90VAC/63HZ	■ON □ OFF	-	PASS
	I/P:264VAC/47HZ	■ON □ OFF	-	PASS
	I/P:264VAC/63HZ	■ON □ OFF	-	PASS
6.4. Switching Test	Switching Time: 0.5 Sec MIN Load / Full Load	@90VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@115VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@230VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@264VAC ■ON □ OFF	-	PASS
6.5. Efficiency	I/P:115VAC O/P:5A	@88%Min Average Efficiency(for four Load)	88.231%	PASS
	I/P:230VAC O/P:5A	@88%MinAverage Efficiency(for four Load)	88.237%	PASS
6.6. Line Regulation	I/P:90VAC~264VAC	<±1%	0.083%	PASS
6.7. Load Regulation	I/P:115VAC O/P:MIN~FULL LOAD	<±5%	3.23%	PASS
	I/P:230VAC O/P:MIN~FULL LOAD	<±5%	2.525%	PASS
6.8. Over-Voltage Protection	I/P:230VAC O/P:MIN LOAD	V1 : 13~18 (MAX)	-	-
6.9. Over-Current Protection	O/P: 12V	10A(MAX)	6.5A	PASS
6.10. Over-Load Protection	I/P:90VAC O/P:MIN LOAD	200%	121.8%	PASS
	I/P:115VAC O/P:MIN LOAD	200%	130%	PASS
	I/P:230VAC O/P:MIN LOAD	200%	134%	PASS
	I/P:264VAC O/P:MIN LOAD	200%	128%	PASS
6.11. Short Circuit Protect	I/P:115VAC O/P:MIN LOAD	12V&GND Short	-	PASS
	I/P:230VAC O/P:MIN LOAD	12V&GND Short	-	PASS

<b>6.12. Line Voltage Surge</b>	O/P: FULL LOAD	Surge voltage from 132VAC to 147VAC (0.5sec), back to 132VAC	-	PASS
	O/P: FULL LOAD	Surge voltage from 264VAC to 293VAC (0.5sec), back to 264VAC	-	PASS
<b>6.13. Line Voltage Sag</b>	O/P: FULL LOAD	Sag voltage from 108VAC to 80VAC (0.5sec), back to 108VAC	-	PASS
	O/P: FULL LOAD	Sag voltage from 198VAC to 161VAC (0.5sec), back to 198VAC	-	PASS
<b>6.14. Ripple &amp; Noise</b>	I/P:115VAC O/P:FULL LOAD	$\leq 150\text{mv}$	48.4mv	PASS
	I/P:230VAC O/P:FULL LOAD	$\leq 150\text{mv}$	48.4mv	PASS
<b>6.15. Setup Time</b>	I/P:90VAC O/P:FULL LOAD	3S(MAX)	1.2ms	PASS
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	748ms	-
<b>6.16. Hold up Time</b>	I/P:115VAC O/P:FULL LOAD	8mS(MIN)	19.2ms	PASS
	I/P:230VAC O/P:FULL LOAD	20mS(MIN)	55ms	PASS
<b>6.17. Rise Time</b>	I/P:115VAC O/P:FULL LOAD	40mS(MAX)	10.132ms	PASS
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	9.207ms	-
<b>6.18. Turn on Overshoot</b>	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
<b>6.19. Turn off Undershoot</b>	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
<b>6.20. Remote ON/OFF</b>	Simulate TTL signal to test this function		-	-
<b>6.21. Power Good Signal</b>	Shall go high level with a delay of 100~500ms		-	-
<b>6.22. Power Consumption Test with AC Adapter</b>	No Run Prime95	I/P:100VAC 0.21A 8.6W	O/P : 12V/0.42 A 5.04W	PASS
	Run Prime 95	I/P:100VAC 0.34A 15W	O/P : 12V/0.85A 10.2W	PASS
	Sleep mode(S3)	I/P:100VAC 0.03A	1.1W	PASS
	Off mode	I/P:100VAC 0.03A	1W	PASS