

Report NO: 14P0A0008_I

FSP120-AAB TEST WITH AEC-6950 Power Electronics Test Report

Summary	<input checked="" type="checkbox"/> Passed <input type="checkbox"/> Failed <input type="checkbox"/> Passed with Deviation Comment: _____			
Test Result Summary				
	Critical	Major	Minor	Enhancement
Defect Found	0	0	0	0
Defect Unsolved	0	0	0	0

Issue date	Approval	Test Engineer
07/09/2014	Tom Lin	Sean Hsu

Table of Contents

1. Project.....	3
2. Power Manufacturer	3
3. Team Member	3
4. Test Equipment.....	3
5. AC Adapter Spec.....	3
6. Test Item.....	4
6.1. AC Input Current.....	4
6.2. MAX Inrush Current	4
6.3. Input Frequency & Voltage	4
6.4. Switching Test.....	4
6.5. Efficiency	4
6.6. Line Regulation.....	4
6.7. Load Regulation	4
6.8. Over-Voltage Protection	4
6.9. Over-Current Protection	4
6.10. Over-Load Protection	4
6.11. Short Circuit Protect.....	4
6.12. Line Voltage Surge.....	4
6.13. Line Voltage Sag	5
6.14. Ripple & Noise.....	5
6.15. Setup Time	5
6.16. Hold up Time.....	5
6.17. Rise Time.....	5
6.18. Turn on Overshoot	5
6.19. Turn off Undershoot	5
6.20. Remote ON/OFF	5
6.21. Power Good Signal.....	5
6.22. Power On In Low Temperature	5
6.23. Power On In High Temperature	5
6.24. Power Consumption Test with DC Power	5
6.25. Power Consumption Test with AC Adapter	5

1. Project

FSP120-AAB AC-DC Adapter for AEC-6950
R1.0 (A950AM10) (05/08/2014)

2. Power Manufacturer

FSP

3. Team Member

PM : Alan Chou ; H/W : Howard Kuo

4. Test Equipment

- 4.1. CPU Board : COM-QM77 REV.B1.0
- 4.2. Carrier Board : DTXP695012 A0.3
- 4.3. CPU : INTEL , CORE I7-3517UE 2.2GHz
- 4.4. HDD : TOSHIBA , MK1661GSYN , 160GB
- 4.5. Memory : DSL , DDR3- 1066 4GB
- 4.6. LCD Monitor : CHIMEI , Model : A170E2-T08
- 4.7. USB Mouse : LOGITECH , Model : M-BT85
- 4.8. USB Keyboard : LOGITECH , Model : Y-BL49

5. AC Adapter Spec

AC Input : 100VAC~240VAC / 47Hz~63Hz

DC Output : 19Vdc Min Load : 0A ; Max Load : 6.32A / 120W

6. Test Item

Test Item	Test Condition / Specification		Sanction	
			Measured	Result
6.1. AC Input Current	I/P:115VAC	1.7A	1.18A	Passed
6.2. MAX Inrush Current	I/P:115VAC	A	14.8A	N/A
	I/P:230VAC	220A	18.3A	Passed
6.3. Input Frequency & Voltage	I/P:90VAC/47HZ	■ON □ OFF	-	Passed
	I/P:90VAC/63HZ	■ON □ OFF	-	Passed
	I/P:264VAC/47HZ	■ON □ OFF	-	Passed
	I/P:264VAC/63HZ	■ON □ OFF	-	Passed
6.4. Switching Test	Switching Time: 0.5 Sec MIN Load / Full Load	@90VAC ■ON □ OFF	-	Passed
	Switching Time: 0.5 Sec MIN Load / Full Load	@115VAC ■ON □ OFF	-	Passed
	Switching Time: 0.5 Sec MIN Load / Full Load	@230VAC ■ON □ OFF	-	Passed
	Switching Time: 0.5 Sec MIN Load / Full Load	@264VAC ■ON □ OFF	-	Passed
6.5. Efficiency	I/P:90VAC FULL LOAD	@86%Min	87.420%	Passed
	I/P:115VAC FULL LOAD	@86%Min	88.987%	Passed
	I/P:230VAC FULL LOAD	@86%Min	89.985%	Passed
	I/P:264VAC FULL LOAD	@86%Min	89.715%	PASS
6.6. Line Regulation	I/P:90VAC~264VAC	<±1%	-0.942%	Passed
6.7. Load Regulation	I/P:115VAC O/P:MINLOAD~FULL LOAD	<±5%	1.12%	Passed
	I/P:230VAC O/P:MINLOAD~FULL LOAD	<±5%	1.71%	Passed
6.8. Over-Voltage Protection	I/P:230VAC O/P:MIN LOAD	V1 : V (MAX)	-	N/A
6.9. Over-Current Protection	O/P: 19V	A(MAX)	8.2A	Passed
6.10. Over-Load Protection	I/P:90VAC O/P:MIN LOAD	%	128.5%	N/A
	I/P:115VAC O/P:MIN LOAD	%	129.8%	N/A
	I/P:230VAC O/P:MIN LOAD	%	128.4%	N/A
	I/P:264VAC O/P:MIN LOAD	%	127.5%	N/A
6.11. Short Circuit Protect	I/P:115VAC O/P:MIN LOAD	19V&GND Short	-	Passed
	I/P:230VAC O/P:MIN LOAD	19V&GND Short	-	Passed
6.12. Line Voltage Surge	O/P: FULL LOAD	Surge voltage from 132VAC to 147VAC (0.5sec), back to 132VAC		Passed
	O/P: FULL LOAD	Surge voltage from 264VAC to 293VAC (0.5sec), back to 264VAC		Passed

6.13. Line Voltage Sag	O/P: FULL LOAD	Sag voltage from 108VAC to 80VAC (0.5sec), back to 108VAC	-	Passed
	O/P: FULL LOAD	Sag voltage from 198VAC to 161VAC (0.5sec), back to 198VDC	-	Passed
6.14. Ripple & Noise	I/P:115VAC O/P:FULL LOAD	$\leq 300\text{mv}$	125.9mv	Passed
	I/P:230VAC O/P:FULL LOAD	$\leq 300\text{mv}$	116.3mv	Passed
6.15. Setup Time	I/P:115VAC O/P:FULL LOAD	mS(MAX)	183ms	N/A
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	184ms	N/A
6.16. Hold up Time	I/P:115VAC O/P:FULL LOAD	8mS(MIN)	33.3ms	Passed
	I/P:230VAC O/P:FULL LOAD	8mS(MIN)	82ms	Passed
6.17. Rise Time	I/P:115VAC O/P:FULL LOAD	mS(MAX)	22.60ms	N/A
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	11.25ms	N/A
6.18. Turn on Overshoot	Turn on overshoot shall not exceed 5% over nominal voltages@ 20 % LOAD		-	Passed
	Turn on overshoot shall not exceed 5% over nominal voltages@ 20 % LOAD		-	Passed
6.19. Turn off Undershoot	Turn off undershoot shall not exceed 5% over nominal voltages@ 20 % LOAD		-	Passed
	Turn off undershoot shall not exceed 5% over nominal voltages@ 20 % LOAD		-	Passed
6.20. Remote ON/OFF	Simulate TTL signal to test this function		-	-
6.21. Power Good Signal	Shall go high level with a delay of 100~500ms		-	-
6.22. Power On In Low Temperature	I/P:115VAC (°C) After 2HR Power On		-	-
6.23. Power On In High Temperature	I/P:115VAC (°C)After 2HR Power On		-	-
6.24. Power Consumption Test with DC Power	No Run Prime95	I/P:9VDC 2.44A 21.96W		Passed
	Run Prime95	I/P:9VDC 3.24A 29.16W		Passed
	No Run Prime95	I/P:30VDC 0.7A 21W		Passed
	Run Prime95	I/P:30VDC 0.95A 28.5W		Passed
6.25. Power Consumption Test with AC Adapter	No Run Prime95	I/P:100VAC 0.24A 25.4W	O/P: 19V/1.14A 21.66W	Passed
	Run Prime95	I/P:100VAC 0.33A 34.2W	O/P: 19V/1.51A 28.69W	Passed
	Sleep Mode	I/P:100VAC 0.07A 6.6W	O/P: 19V/0.3A 5.7W	Passed
	Off Mode	I/P:100VAC 0.07A 6.4W	O/P: 19V/0.29A 5.51W	Passed