

FSP120-AAB of AEC-7450
Power Electronics Test Report

Report NO.: 08P0A0012_I

Wenyuan Yang

Approved By

Oct.01.2008

Date

Sean Hsu

Issued By

Oct.01.2008

Date

Table of Contents

| | |
|--|---|
| 1. Project | 3 |
| 2. Power Manufacturer | 3 |
| 3. Team Member | 3 |
| 4. Test Equipment | 3 |
| 5. Photos of Product | 3 |
| Fig.5.1. —Photos | 3 |
| 6. Test Item | 4 |
| 6.1. AC Input Current | 4 |
| 6.2. MAX Inrush Current | 4 |
| 6.3. Input Frequency & Voltage | 4 |
| 6.4. Switching Test | 4 |
| 6.5. Efficiency | 4 |
| 6.6. Line Regulation | 4 |
| 6.7. Load Regulation | 4 |
| 6.8. Over-Voltage Protection | 4 |
| 6.9. Over-Circuit Protection | 4 |
| 6.10. Over-Load Protection | 4 |
| 6.11. Short Circuit Protect | 4 |
| 6.12. Line Voltage Surge | 4 |
| 6.13. Line Voltage Sag | 4 |
| 6.14. Ripple & Noise | 4 |
| 6.15. Setup Time | 4 |
| 6.16. Hold up Time | 4 |
| 6.17. Rise Time | 4 |
| 6.18. Turn on Overshoot | 4 |
| 6.19. Turn off Undershoot | 5 |
| 6.20. Remote ON/OFF | 5 |
| 6.21. Power Good Signal | 5 |
| 6.22. Power On In Low Temperature | 5 |
| 6.23. Power On In High Temperature | 5 |
| 6.24. Room Burn-in test | 5 |
| 6.25. On/Off Cycling | 5 |
| 6.26. Power Consumption Test | 5 |
| 7. Test Result and Observation | 5 |

1. Project

FSP120-AAB AC-DC Adapter for AEC-7450

2. Power Manufacturer

FSP

3. Team Member

PM : Ivan Lin ; PPC H/W : Kevin Liu

4. Test Equipment

- 4.1. EPIC PCB : Fastwel CPC800-0.1 (BIOS: CPC800 V1.36)
- 4.2. CPU : Onboard Intel Pentium M 1.8GHz
- 4.3. Memory : Onboard DDR1GB / K4H510838B-G(Z)C/LB3
- 4.4. Wide Temp. SSD SATA HDD : Habiwara 4GB / Industrial
- 4.5. AC Adapter : FSP120-AAB O/P: 19V/6.32A

5. Photos of Product

Fig.5.1. —Photos



6. Test Item

| Test Item | Test Condition / Specification | | Sanction | |
|--------------------------------|--|--|----------|--------|
| | | | Measured | Result |
| 6.1. AC Input Current | I/P:90VAC | A | 1.53A | - |
| 6.2. MAX Inrush Current | I/P:115VAC | A | 11.7A | - |
| | I/P:230VAC | A | 18.3A | - |
| 6.3. Input Frequency & Voltage | I/P:90VAC/47HZ | ■ON □ OFF | - | PASS |
| | I/P:90VAC/63HZ | ■ON □ OFF | - | PASS |
| | I/P:264VAC/47HZ | ■ON □ OFF | - | PASS |
| | I/P:264VAC/63HZ | ■ON □ OFF | - | PASS |
| 6.4. Switching Test | Switching Time: 0.5 Sec MIN Load / Full Load | @90VAC ■ON □ OFF | - | PASS |
| | Switching Time: 0.5 Sec MIN Load / Full Load | @115VAC ■ON □ OFF | - | PASS |
| | Switching Time: 0.5 Sec MIN Load / Full Load | @230VAC ■ON □ OFF | - | PASS |
| | Switching Time: 0.5 Sec MIN Load / Full Load | @264VAC ■ON □ OFF | - | PASS |
| 6.5. Efficiency | I/P:90VAC FULL LOAD | @86%Min | 86.678% | PASS |
| | I/P:115VAC FULL LOAD | @86%Min | 88.115% | PASS |
| | I/P:230VAC FULL LOAD | @86%Min | 89.422% | PASS |
| | I/P:264VAC FULL LOAD | @86%Min | 89.106% | PASS |
| 6.6. Line Regulation | I/P:90VAC~264VAC | <±1% | 0.421% | PASS |
| 6.7. Load Regulation | I/P:115VAC O/P:MINLOAD~FULL LOAD | <±5% | 1.105 | PASS |
| | I/P:230VAC O/P:MINLOAD~FULL LOAD | <±5% | 1.473 | PASS |
| 6.8. Over-Voltage Protection | I/P:230VAC O/P:MIN LOAD | V1 : (MAX) | - | - |
| 6.9. Over-Circuit Protection | O/P: 19V | A(MAX) | 8.58A | - |
| 6.10. Over-Load Protection | I/P:90VAC O/P:MIN LOAD | % | 136.008 | - |
| | I/P:115VAC O/P:MIN LOAD | % | 134.58 | - |
| | I/P:230VAC O/P:MIN LOAD | % | 150.416 | - |
| | I/P:264VAC O/P:MIN LOAD | % | 152.00 | - |
| 6.11. Short Circuit Protect | I/P:115VAC O/P:MIN LOAD | 19V&GND Short | - | PASS |
| | I/P:230VAC O/P:MIN LOAD | 19V&GND Short | - | PASS |
| 6.12. Line Voltage Surge | O/P: FULL LOAD | Surge voltage from 132VAC to 147VAC (0.5sec), back to 132VDC | - | PASS |
| | O/P: FULL LOAD | Surge voltage from 264VAC to 293VAC (0.5sec), back to 264VAC | - | PASS |
| 6.13. Line Voltage Sag | O/P: FULL LOAD | Sag voltage from 108VAC to 80VAC (0.5sec), back to 108VAC | - | PASS |
| | O/P: FULL LOAD | Sag voltage from 198VAC to 161VAC (0.5sec), back to 198VDC | - | PASS |
| 6.14. Ripple & Noise | I/P:115VAC O/P:FULL LOAD | ≤300mv | 121.9 | PASS |
| | I/P:230VAC O/P:FULL LOAD | ≤300mv | 106.3 | PASS |
| 6.15. Setup Time | I/P:115VAC O/P:FULL LOAD | mS(MAX) | 175 | - |
| | I/P:230VAC O/P:FULL LOAD | mS(MAX) | 176.75 | - |
| 6.16. Hold up Time | I/P:115VAC O/P:FULL LOAD | 8mS(MIN) | 31.1 | PASS |
| | I/P:230VAC O/P:FULL LOAD | 8mS(MIN) | 29.8 | PASS |
| 6.17. Rise Time | I/P:115VAC O/P:FULL LOAD | mS(MAX) | 12.8 | - |
| | I/P:230VAC O/P:FULL LOAD | mS(MAX) | 12.6 | - |
| 6.18. Turn on Overshoot | Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD | | - | PASS |
| | Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD | | - | PASS |

| | | | | |
|------------------------------------|--|------------------------|------------------|------|
| 6.19. Turn off Undershoot | Turn off undershoot shall not exceed 10% over nominal voltages | | - | PASS |
| | Turn off undershoot shall not exceed 10% over nominal voltages | | - | PASS |
| 6.20. Remote ON/OFF | Simulate TTL signal to test this function | | | - |
| 6.21. Power Good Signal | Shall go high level with a delay of 100~500ms | | - | - |
| 6.22. Power On In Low Temperature | I/P: 115VAC (0°C) After 2HR Power On | | | - |
| 6.23. Power On In High Temperature | I/P: 115VAC (50°C) After 2HR Power On | | | - |
| 6.24. Room Burn-in test | I/P: 115VAC O/P: FULL LOAD TA: 25°C BURN-IN DURATION : 2 hour | | | PASS |
| 6.25. On/Off Cycling | Times / on: 20 sec / off: 10 sec | | | - |
| 6.26. Power Consumption Test | No Run Prime95 | I/P: 90VAC 0.25A 22.7W | O/P: 19V/95.64mA | PASS |
| | Run Prime95 | I/P: 90VAC 0.35A 35.3W | O/P: 19V/206.9mA | PASS |

7. Test Result and Observation

No fault was found during the test