

FSP084-DMAA1 of AGD-315D Power Electronics Test Report

Summary	<input checked="" type="checkbox"/> Pass <input type="checkbox"/> Fail <input type="checkbox"/> Pass with Deviation Comment: _____			
Test Result Summary				
	Critical	Major	Minor	Enhancement
Defect Found	0	0	0	0
Defect Unsolved	0	0	0	0

Issue date	Approval	Test Engineer
08/01/2011	Jansin Lee	Matthew Chi

Table of Contents

1. Project.....	3
2. Power Manufacturer	3
3. Team Member	3
4. Test Equipment	3
5. AC Adapter Spec.....	3
6. Test Item	4
6.1. AC Input Current.....	4
6.2. MAX Inrush Current	4
6.3. Input Frequency & Voltage	4
6.4. Switching Test.....	4
6.5. Efficiency.....	4
6.6. Line Regulation.....	4
6.7. Load Regulation	4
6.8. Over-Voltage Protection	4
6.9. Over-Circuit Protection	4
6.10. Over-Load Protection	4
6.11. Short Circuit Protect.....	4
6.12. Line Voltage Surge.....	4
6.13. Line Voltage Sag	5
6.14. Ripple & Noise.....	5
6.15. Setup Time	5
6.16. Hold up Time.....	5
6.17. Rise Time.....	5
6.18. Turn on Overshoot	5
6.19. Turn off Undershoot.....	5
6.20. Remote ON/OFF	5
6.21. Power Good Signal.....	5
6.22. Power On In Low Temperature	5
6.23. Power On In High Temperature	5
6.24. System Power Consumption Test	5

1. Project

FSP084-DMAA1 AC-DC Adapter for AGD-315D

2. Power Manufacturer

FSP

3. Team Member

PM : Maiya Cheng ; PPC H/W : Jack Peng

4. Test Equipment

- 4.1. Panel : AUO 15" XGA 250 nits CCFL backlight
- 4.2. USB Mouse : Logitech , Model : M-BT85
- 4.3. USB Keyboard : Logitech , Model : Y-BL49
- 4.4. CPU Board : EMB-9458T A1.0
- 4.5. Memory : Kingston KVR667D2N5 / 512M *2
- 4.6. HDD : Seagate ST3160811AS 160G SATAII 3.5"
- 4.7. Power Supply : FSP084-DMAA1 AC-DC Power for AGD-315D

5. AC Adapter Spec

AC Input : 90VAC~264VAC / 47Hz~63Hz

DC Output : 12Vdc Min Load : 0A Full Load : 7A / 84W

6. Test Item

Test Item	Test Condition / Specification		Sanction	
			Measured	Result
6.1. AC Input Current	I/P:115VAC	1.3A	0.991A	PASS
6.2. MAX Inrush Current	I/P:115VAC	A	4.57A	-
	I/P:230VAC	A	6.32A	-
6.3. Input Frequency & Voltage	I/P:90VAC/47HZ	■ON □ OFF	-	PASS
	I/P:90VAC/63HZ	■ON □ OFF	-	PASS
	I/P:264VAC/47HZ	■ON □ OFF	-	PASS
	I/P:264VAC/63HZ	■ON □ OFF	-	PASS
6.4. Switching Test	Switching Time: 0.5 Sec MIN Load / Full Load	@90VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@115VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@230VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@264VAC ■ON □ OFF	-	PASS
6.5. Efficiency	I/P:90VAC O/P:5A	@83%Min	86.007%	PASS
	I/P:115VAC O/P:5A	@83%Min	87.355%	PASS
	I/P:230VAC O/P:5A	@83%Min	87.029%	PASS
	I/P:264VAC O/P:5A	@83%Min	86.674%	PASS
6.6. Line Regulation	I/P:90VAC~264VAC	<%	0.042%	-
6.7. Load Regulation	I/P:115VAC O/P:MIN~FULL LOAD	<%	1.975	-
	I/P:230VAC O/P:MIN~FULL LOAD	<%	2.042	-
6.8. Over-Voltage Protection	I/P:230VAC O/P:MIN LOAD	V1 : 17 (MAX)	-	-
6.9. Over-Circuit Protection	O/P: 12V	9.4A(MAX)	8.4A	PASS
6.10. Over-Load Protection	I/P:90VAC O/P:MIN LOAD	135%	120%	PASS
	I/P:115VAC O/P:MIN LOAD	135%	122%	PASS
	I/P:230VAC O/P:MIN LOAD	135%	120%	PASS
	I/P:264VAC O/P:MIN LOAD	135%	121%	PASS
6.11. Short Circuit Protect	I/P:115VAC O/P:MIN LOAD	12V&GND Short	-	PASS
	I/P:230VAC O/P:MIN LOAD	12V&GND Short	-	PASS
6.12. Line Voltage Surge	O/P: FULL LOAD	Surge voltage from 132VAC to 147VAC (0.5sec), back to 132VAC	-	PASS
	O/P: FULL LOAD	Surge voltage from 264VAC to 293VAC (0.5sec), back to 264VAC	-	PASS

FSP084-DMAA1 of AGD-315D Power Electronics Test Report

6.13. Line Voltage Sag	O/P: FULL LOAD	Sag voltage from 108VAC to 80VAC (0.5sec), back to 108VAC	-	PASS
	O/P: FULL LOAD	Sag voltage from 198VAC to 161VAC (0.5sec), back to 198VAC	-	PASS
6.14. Ripple & Noise	I/P:115VAC O/P:FULL LOAD	$\leq 150\text{mv}$	110.9mv	PASS
	I/P:230VAC O/P:FULL LOAD	$\leq 150\text{mv}$	93.8mv	PASS
6.15. Setup Time	I/P:115VAC O/P:FULL LOAD	3S(MAX)	729ms	PASS
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	505ms	PASS
6.16. Hold up Time	I/P:115VAC O/P:FULL LOAD	20mS(MIN)	32.6ms	PASS
	I/P:230VAC O/P:FULL LOAD	mS(MIN)	84.5ms	PASS
6.17. Rise Time	I/P:115VAC O/P:FULL LOAD	mS(MAX)	4.76ms	PASS
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	5.76ms	PASS
6.18. Turn on Overshoot	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
6.19. Turn off Undershoot	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
6.20. Remote ON/OFF	Simulate TTL signal to test this function			-
6.21. Power Good Signal	Shall go high level with a delay of100~500ms			-
6.22. Power On In Low Temperature	I/P:115VAC (0°C) After 2HR Power On			-
6.23. Power On In High Temperature	I/P:115VAC (50°C)After 2HR Power On			-
6.24. System Power Consumption Test	No Run Video(VGA)	I/P:100VAC 0.41A 19.6W	O/P: 12V/1.43A	PASS
	Run Video(VGA)	I/P:100VAC 0.41A 19.6W	O/P: 12V/1.52A	PASS
	No Run Video(DVI)	I/P:100VAC 0.41A 19.7W	O/P: 12V/1.55A	PASS
	Run Video(DVI)	I/P:100VAC 0.42A 20.0W	O/P: 12V/1.58A	PASS