

Report NO: 13I0A0012\_I

# ENP-7140SH2 of NVR-B75 Power Electronics Test Report

Summary	<input checked="" type="checkbox"/> <b>Pass</b> <input type="checkbox"/> <b>Fail</b> <input type="checkbox"/> <b>Pass with Deviation</b> <b>Comment:</b> _____			
<b>Test Result Summary</b>				
	Critical	Major	Minor	Enhancement
Defect Found	0	0	0	0
Defect Unsolved	0	0	0	0

Issue date

**08/14/2013**

Approval

**Tom Lin**

Test Engineer

**Sean Hsu**

## Table of Contents

1.	Project.....	3
2.	Power Manufacturer .....	3
3.	Team Member .....	3
4.	Test Equipment .....	3
5.	AC Adapter Spec.....	3
6.	Test Item .....	4
6.1.	AC Input Current.....	4
6.2.	MAX Inrush Current .....	4
6.3.	Input Frequency & Voltage .....	4
6.4.	Switching Test.....	4
6.5.	Efficiency .....	4
6.6.	Line Regulation.....	4
6.7.	Load Regulation .....	4
6.8.	Over-Voltage Protection .....	4
6.9.	Over-Circuit Protection .....	4
6.10.	Over-Load Protection .....	5
6.11.	Short Circuit Protect.....	5
6.12.	Line Voltage Surge.....	5
6.13.	Line Voltage Sag .....	5
6.14.	Ripple & Noise .....	5
6.15.	Setup Time .....	5
6.16.	Hold up Time.....	5
6.17.	Rise Time.....	5
6.18.	Turn on Overshoot .....	5
6.19.	Turn off Undershoot.....	6
6.20.	Remote ON/OFF .....	6
6.21.	Power Good Signal.....	6
6.22.	Power Fall Signal .....	6
6.23.	Power On In Low Temperature .....	6
6.24.	Power On In High Temperature .....	6
6.25.	Room Burn-in test .....	6
6.26.	On/Off Cycling .....	6
6.27.	Power Consumption Test.....	6

**1. Project**

ENP-7140SH2 AC-DC Power for NVR-B75

**2. Power Manufacturer**

Enhance

**3. Team Member**

PM : Jason Liu ; H/W : Gary Lin

**4. Test Equipment**

4.1. CPU Board : AAEON , EMB-B75A-A10

4.2. CPU : INTEL , Core I5-3550S 3.0GHz

4.3. HDD : WD , WD3200AAKX 320GB\*6

4.4. Memory : DSL , DDR3- 1333 4GB

4.5. Power Supply : Enhance , M/N : ENP-7140SH2 , O/P : 400Watt

4.6. LCD Monitor : CHIMEI , Model : A170E2-T08

4.7. USB Keyboard : Logitech , Model : Y-BL49

4.8. USB Mouse : Logitech , Model : M-BT85

**5. AC Adapter Spec**

AC Input : 100VAC~240VAC / 47Hz~63Hz

DC Output : 400W

## 6. Test Item

Test Item	Test Condition / Specification		Sanction	
			Measured	Result
6.1. AC Input Current	I/P:100VAC	6A	5.6A	PASS
6.2. MAX Inrush Current	I/P:115VAC	A	A	N/A
	I/P:230VAC	A	A	N/A
6.3. Input Frequency & Voltage	I/P:90VAC/47HZ	■ON □ OFF	-	PASS
	I/P:90VAC/63HZ	■ON □ OFF	-	PASS
	I/P:264VAC/47HZ	■ON □ OFF	-	PASS
	I/P:264VAC/63HZ	■ON □ OFF	-	PASS
6.4. Switching Test	Switching Time: 0.5 Sec MIN Load / Full Load	@90VAC □ON □ OFF	-	N/A
	Switching Time: 0.5 Sec MIN Load / Full Load	@115VAC □ON □ OFF	-	N/A
	Switching Time: 0.5 Sec MIN Load / Full Load	@230VAC □ON □ OFF	-	N/A
	Switching Time: 0.5 Sec MIN Load / Full Load	@264VAC □ON □ OFF	-	N/A
6.5. Efficiency	I/P:115VAC FULL LOAD	@87%Min	87.2%	PASS
	I/P:230VAC FULL LOAD	@87%Min	87.9%	PASS
6.6. Line Regulation	I/P:90VAC~264VAC	<±5%(3.3V)	0.8%	PASS
		<±5%(5V)	0.6%	PASS
		<±5%(12V)	0.8%	PASS
		<±10%(-12V)	1.2%	PASS
		<±5%(5VSB)	0.5%	PASS
6.7. Load Regulation	I/P:115VAC O/P:MINLOAD~FULL LOAD	<±5%(3.3V)	1.45/-2.9%	PASS
		<±5%(5V)	1.68/-4.4%	PASS
		<±5%(12V)	0.25/0.375%	PASS
		<±10%(-12V)	-0.78/2.21%	PASS
		<±5%(5VSB)	0.95/-2.2%	PASS
	I/P:230VAC O/P:MINLOAD~FULL LOAD	<±5%(3.3V)	1.44/-2.95%	PASS
		<±5%(5V)	1.75/-4.4%	PASS
		<±5%(12V)	0.17/0.38%	PASS
		<±10%(-12V)	-0.88/-2.4%	PASS
		<±5%(5VSB)	0.9/-2.2%	PASS
6.8. Over-Voltage Protection	I/P:230VAC O/P:MIN LOAD	V1 : 5.1V	-	N/A
		V2 : 7V	-	N/A
		V3 : 16.5V	-	N/A
6.9. Over-Circuit Protection	O/P: 3.3V	50A(MAX)	43	PASS
	O/P: 5V	50A(MAX)	42%	PASS
	O/P: 12V	45A(MAX)	-	N/A

6.10. Over-Load Protection	I/P:90VAC O/P:MIN LOAD	-	-	-
	I/P:115VAC O/P:MIN LOAD	-	-	-
	I/P:230VAC O/P:MIN LOAD	-	-	-
	I/P:264VAC O/P:MIN LOAD	-	-	-
6.11. Short Circuit Protect	I/P:115VAC O/P:MIN LOAD	5V&GND Short	-	PASS
	I/P:230VAC O/P:MIN LOAD	5V&GND Short	-	PASS
6.12. Line Voltage Surge	O/P: FULL LOAD	Surge voltage from 132VAC to 147VAC (0.5sec), back to 132VDC	-	PASS
	O/P: FULL LOAD	Surge voltage from 264VAC to 293VAC (0.5sec), back to 264VAC	-	PASS
6.13. Line Voltage Sag	O/P: FULL LOAD	Sag voltage from 108VAC to 80VAC (0.5sec), back to 108VAC	-	PASS
	O/P: FULL LOAD	Sag voltage from 198VAC to 161VAC (0.5sec), back to 198VDC	-	PASS
6.14. Ripple & Noise	I/P:115VAC O/P:FULL LOAD	$\leq 50\text{mv}(3.3\text{V})$	48.7mv	PASS
		$\leq 50\text{mv}(5\text{V})$	42.4mv	PASS
		$\leq 120\text{mv}(12\text{V})$	83.7mv	PASS
		$\leq 120\text{mv}(-12\text{V})$	118.5mv	PASS
	I/P:230VAC O/P:FULL LOAD	$\leq 50\text{mv}(5\text{VSB})$	35.5mv	PASS
		$\leq 50\text{mv}(3.3\text{V})$	47.7mv	PASS
		$\leq 50\text{mv}(5\text{V})$	40.5mv	PASS
		$\leq 120\text{mv}(12\text{V})$	86.6mv	PASS
		$\leq 120\text{mv}(-12\text{V})$	117.5mv	PASS
		$\leq 50\text{mv}(5\text{VSB})$	36.5mv	PASS
6.15. Setup Time	I/P:115VAC O/P:FULL LOAD	500mS(MAX)(5V)	-	-
	I/P:230VAC O/P:FULL LOAD	500mS(MAX) (5V)	-	-
6.16. Hold up Time	I/P:115VAC O/P:FULL LOAD	16mS(MIN) (5V)	-	-
	I/P:230VAC O/P:FULL LOAD	16mS(MIN) (5V)	-	-
6.17. Rise Time	I/P:115VAC O/P:FULL LOAD	20mS(MAX) (5V)	-	-
	I/P:230VAC O/P:FULL LOAD	20mS(MAX) (5V)	-	-
6.18. Turn on Overshoot	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS
	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	PASS

6.19. Turn off Undershoot	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
6.20. Remote ON/OFF	Simulate TTL signal to test this function			-
6.21. Power Good Signal	Shall go high level with a delay of 100~500ms		389	PASS
6.22. Power Fall Signal			-	-
6.23. Power On In Low Temperature	I/P:115VAC ( 0°C ) After 2HR Power On			-
6.24. Power On In High Temperature	I/P:115VAC ( 40 °C )After 2HR Power On			-
6.25. Room Burn-in test	I/P:115VAC O/P: FULL LOAD TA:25 °C BURN-IN DURATION : 2 hour			-
6.26. On/Off Cycling	Times / on: 20 sec / off: 10 sec			-
6.27. Power Consumption Test	No Run Prime95	I/P: 100 VAC 0.67 A 65.4W	O/P: 3.3V/1.65A 5V/3.31A 12V/3.01A -12V/0.03A 5VSB/0.03A Total:58.63W	PASS
	Run Prime95	I/P: 100 VAC 0.93A 91.6W	O/P: 3.3V/1.65A 5V/3.98A 12V/4.49A -12V/0.03A 5VSB/0.03A Total:79.74W	PASS