

Report No: 15P0A0011_I

FSP120-ABAN2 with OMNI-2155 Power Electronics Test Report

Summary	<input checked="" type="checkbox"/> Pass <input type="checkbox"/> Fail <input type="checkbox"/> Pass with Deviation Comment:			
Test Result Summary				
	Critical	Major	Minor	Enhancement
Defect Found	0	0	0	0
Defect Unsolved	0	0	0	0

Issue date	Approval	Test Engineer
09/04/2015	KJ Wang	Mike Lee

Table of Contents

1. Project.....	3
2. Power Manufacturer	3
3. Team Member	3
4. Test Equipment.....	3
5. AC Adapter Spec.....	3
6. Test Item.....	4
6.1. AC Input Current.....	4
6.2. MAX Inrush Current	4
6.3. Input Frequency & Voltage	4
6.4. Switching Test.....	4
6.5. Efficiency	4
6.6. Line Regulation.....	4
6.7. Load Regulation	4
6.8. Over-Voltage Protection	4
6.9. Over-Current Protection	4
6.10. Over-Load Protection	4
6.11. Short Circuit Protect.....	4
6.12. Ripple & Noise.....	5
6.13. Turn-On Delay Time.....	5
6.14. Hold up Time.....	5
6.15. Rise Time.....	5
6.16. Turn on Overshoot	5
6.17. Turn off Undershoot.....	5
6.18. Power Consumption Test with DC Power	5
6.19. Power Consumption Test with AC Adapter	5

1. Project

FSP120-ABAN2 AC-DC Adapter for OMNI-2155

2. Power Manufacturer

FSP

3. Team Member

PM : Tim Lin ; H/W : Howard Kuo

4. Test Equipment

4.1. LCD Monitor : AUO , Model : G156XW01 V1

4.2. PCB Board : AAEON , PBA-BT03 Rev.A0.2

4.3. CPU : Intel ® Celeron ® Processor J1900 @ 1.99GHz (2M Cache, up to 2.42 GHz)

4.4. HDD : TOSHIBA 2.5" SATA HDD 100G - MK1060GSC

4.5. Memory : Memphis DDR3L-1600 SODIMM 8GB - I'M.IM4G08D3FABG-125I

4.6. Power Supply : DC 9~30V (9V use PSW 160-21.6 (GWINSTEK))

5. AC Adapter Spec

AC Input : 90VAC~264VAC / 47Hz~63Hz

DC Output : 19VDC Min Load : 0A Full Load : 6.32A / 120.08W

6. Test Item

Test Item	Test Condition / Specification		Sanction	
			Measured	Result
6.1. AC Input Current	I/P:100VAC	$\leq 1.8A$	1.31A	PASS
	I/P:240VAC	$\leq 1.8A$	0.57A	PASS
6.2. MAX Inrush Current	I/P:100VAC	A	7.81A	-
	I/P:240VAC	A	8.52A	-
6.3. Input Frequency & Voltage	I/P:90VAC/47HZ	■ON □ OFF	-	PASS
	I/P:90VAC/63HZ	■ON □ OFF	-	PASS
	I/P:264VAC/47HZ	■ON □ OFF	-	PASS
	I/P:264VAC/63HZ	■ON □ OFF	-	PASS
6.4. Switching Test	Switching Time: 0.5 Sec MIN Load / Full Load	@90VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@115VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@230VAC ■ON □ OFF	-	PASS
	Switching Time: 0.5 Sec MIN Load / Full Load	@264VAC ■ON □ OFF	-	PASS
6.5. Efficiency	I/P:100VAC O/P:6.32 A	@ $\geq 87\%$ Min Average Efficiency	90.464%	PASS
	I/P:240VAC O/P:6.32A	@ $\geq 89\%$ MinAverage Efficiency	91.726%	PASS
6.6. Line Regulation	I/P:100VAC~240VAC	< $\pm 5\%$	0	PASS
6.7. Load Regulation	I/P:100VAC O/P:MIN~FULL LOAD	< $\pm 5\%$	-1.832%	PASS
	I/P:240VAC O/P:MIN~FULL LOAD	< $\pm 5\%$	-1.789%	PASS
6.8. Over-Voltage Protection	I/P:240VAC O/P:MIN LOAD	29V (MAX)	-	-
6.9. Over-Current Protection	O/P: 19V	-	8.5A	-
6.10. Over-Load Protection	I/P:100VAC O/P:MIN LOAD	-	134%	-
	I/P:240VAC O/P:MIN LOAD	-	134%	-
6.11. Short Circuit Protect	I/P:100VAC O/P:MIN LOAD	19V&GND Short	-	PASS
	I/P:240VAC O/P:MIN LOAD	19V&GND Short	-	PASS

6.12. Ripple & Noise	I/P:100VAC O/P:FULL LOAD	$\leq 350m$ Vp-p	160.9mv	PASS
	I/P:240VAC O/P:FULL LOAD	$\leq 350m$ Vp-p	140.6mv	PASS
6.13. Turn-On Delay Time	I/P:100VAC O/P:FULL LOAD	$\leq 3Sec$ (MAX)	642.5ms	PASS
6.14. Hold up Time	I/P:100VAC O/P:FULL LOAD	$\geq 10mS$ (MIN)	30.9ms	PASS
	I/P:240VAC O/P:FULL LOAD	$\geq 10mS$ (MIN)	65.25ms	PASS
6.15. Rise Time	I/P:100VAC O/P:FULL LOAD	$\leq 50mS$ (MAX)	16.3ms	PASS
6.16. Turn on Overshoot	Turn on overshoot shall not exceed 10% over nominal voltages@ 0 % & MAX LOAD		-	PASS
	Turn on overshoot shall not exceed 10% over nominal voltages@ 0 % & MAX LOAD		-	PASS
6.17. Turn off Undershoot	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
	Turn off undershoot shall not exceed 10% over nominal voltages		-	PASS
6.18. Power Consumption Test with DC Power	No Run Prime 95	I/P:9VDC 1.91A 17.19W		PASS
	Run Prime 95	I/P:9VDC 2.50A 22.5W		PASS
	No Run Prime 95	I/P:30VDC 0.68A 20.4W		PASS
	Run Prime 95	I/P:30VDC 0.83A 24.9W		PASS
6.19. Power Consumption Test with AC Adapter	No Run Prime95	I/P : 100VAC 0.48A 22.2W	O/P : 19V/0.94A 17.86W	PASS
	Run Prime 95	I/P : 100VAC 0.57A 26.4W	O/P : 19V/1.22A 23.18W	PASS
	Sleep mode(S3)	I/P : 100VAC 0.04A 1.5W	O/P : 19V/0.07A 1.33W	PASS
	Off mode	I/P : 100VAC 0.03A 1.3W	O/P : 19V/0.05A 0.95W	PASS