

■ PC/104 Ethernet Module



Features

- Hardware and Software Compatible with Novell® NE2000
- Automatically Detects 8-bit or 16-bit Data Bus
- Pure PC/104 Interface for 10Base-T Ethernet

Ordering Information

- **TF-PCM-3660-B10**
PC/104 Board 10Base-T Ethernet Module

Specifications

I/O Address	200, 220, 240, 260, 280, 2A0, 2C0, 300, 320, 340, 380, 3A0
Interrupt Level	IRQ 3,4,5,9,10,11,12 or 15
Boot ROM Address	C0000, C8000, D0000 or D8000H (Optional)
Data Bus	8-bit, 16-bit, or auto-sensing
Standard	IEEE 802.3 10Mbps CSMA/CD 10Base-T Transceiver
Power Consumption	+5V@400mA max
Operating Temperature	32°F ~ 140°F (0°C ~ 60°C)

PCM-3115C

■ PC/104 2-slot PCMCIA Module



Features

- PCMCIA Socket Supports Two Type I/II Cards or One Type III Card
- Bootable Function From Linear Flash Card, ATA Card and SRAM Card

Ordering Information

- **TF-PCM-3115C**
PC/104 Board 2-slot PCMCIA Module

Specifications

Standard	Complies with PCMCIA v.2.1 and JEIDA v4.2
Memory	Programmable 8KB boot FLASH ROM
Interface	16-bit data bus
Indicator	Busy status LED
Power Requirement	+5V

PCMCIA Modules