

➤ Passive Backplanes

Passive Backplanes Ordering Information

Model Name	Backplane Type	Slots						Power Connector	Configuration Standard
		Total	PCISA	PCI	ISA	PICMG	System		
BP-202SG-P1-A10	PCI/ISA	2		1		1	Single	+/-5V, +/-12V	PICMG
BP-203SI-A10	ISA	3			3		Single	+/-5V, +/-12V	ISA
BP-204SG-P1-A10	PCI/ISA	4		1	2	1	Single	+/-5V, +/-12V	PICMG
BP-204SS-P1-A11	ISA/PCISA	4	2	1	1		Single	+/-5V, +/-12V	PCISA
BP-204SS-P1-A11-01	ISA/PCISA	4	2	1	1		Single	+/-5V, +/-12V	PCISA
BP-204SS-P2-A10	PCI/ISA/PCISA	4	1	1	1	1	Single	+/-5V, +/-12V, +3V	PICMG/PCISA
BP-204SI-A13	ISA	4			4		Single	+/-5V, +/-12V	ISA
BP-204SI-A13-01	ISA	4			4		Single	+/-5V, +/-12V	ISA
BP-204SP-A10	PCI/ISA	4		3		1	Single	+/-5V, +/-12V	PICMG
BP-206SG-P3-V61	PCI/ISA	7		4	1	2	Single	+/-5V, +/-12V, +3V	PICMG
BP-206SI-V60	ISA	6			6		Single	+/-5V, +/-12V	ISA
BP-206SS-P4-A12	PCI/PCISA	6	3	4			Single	+/-5V, +/-12V	PCISA
BP-206SG-P2-V11	PCI/ISA	6		2	3	1	Single	+/-5V, +/-12V	PICMG
BP-206SG-P4-V00	PCI/ISA	6		4	1	1	Single	+/-5V, +/-12V, +3V	PICMG
BP-208SG-P3-A10	PCI/ISA	8		3	4	1	Single	+/-5V, +/-12V	PCI/ISA
BP-208SI-A00	ISA	8			8		Single	+/-5V, +/-12V	ISA
BP-208SS-P4-V10	PCI/ISA/PCISA	8	2	2	4		Single	+/-5V, +/-12V	PCISA
BP-209SG-P4-V61	PCI/ISA	9		4	3	2	Single	+/-5V, +/-12V, +3V	PICMG
BP-213DG-P6-V60	PCI/ISA	13		7	4	3	Dual	+/-5V, +/-12V, +3V	PICMG
BP-214DI-V60	ISA	14			14		Dual	+/-5V, +/-12V	ISA
BP-214SG-P4-V65	PCI/ISA	14		4	8	2	Single	+/-5V, +/-12V, +3V	PICMG
BP-214SG-P7-V22	PCI/ISA	14		7	5	2	Single	+/-5V, +/-12V, +3V	PICMG
BP-214SI-V61	ISA	14			14		Single	+/-5V, +/-12V	ISA
BP-214SS-P4-V11	ISA/PCISA	14	2	4	8		Single	+/-5V, +/-12V, +3V	PCISA
BP-218-DG-P8-V61	PCI/ISA	18		8	6	4	Dual	+/-5V, +/-12V, +3V	PICMG
BP-219SG-P4-V60	PCI/ISA	19		4	13	2	Single	+/-5V, +/-12V, +3V	PICMG
BP-220DI-V60	ISA	20			20		Dual	+/-5V, +/-12V	ISA
BP-220Q1-V60	ISA	20			20		Four	+/-5V, +/-12V	ISA
BP-220SI-V60	ISA	20			20		Single	+/-5V, +/-12V	ISA