

Report NO: 13R0A0008_I

LTE24E-S2-2 of RTC-700C Power Electronics Test Report

Summary	<input checked="" type="checkbox"/> Passed			
	<input type="checkbox"/> Failed			
<input type="checkbox"/> Passed with Deviation				
Comment: _____				
Test Result Summary				
	Critical	Major	Minor	Enhancement
Defect Found	0	0	0	0
Defect Unsolved	0	0	0	0

Issue date

11/27/2013

Approval

Tom Lin

Test Engineer

Sean Hsu

Table of Contents

1. Project.....	3
2. Power Manufacturer	3
3. Team Member	3
4. Test Equipment	3
5. AC Adapter Spec.....	3
6. Test Item.....	4
6.1. AC Input Current.....	4
6.2. MAX Inrush Current	4
6.3. Input Frequency & Voltage	4
6.4. Switching Test.....	4
6.5. Efficiency	4
6.6. Line Regulation.....	4
6.7. Load Regulation	4
6.8. Over-Voltage Protection	4
6.9. Over-Circuit Protection	4
6.10. Over-Load Protection	4
6.11. Short Circuit Protect.....	4
6.12. Line Voltage Surge.....	4
6.13. Line Voltage Sag	5
6.14. Ripple & Noise.....	5
6.15. Setup Time	5
6.16. Hold up Time.....	5
6.17. Rise Time.....	5
6.18. Turn on Overshoot	5
6.19. Turn off Undershoot.....	5
6.20. Remote ON/OFF	5
6.21. Power Good Signal.....	5
6.22. Power On In Low Temperature	5
6.23. Power On In High Temperature	5
6.24. Power Consumption Test with AC Adapter	5

1. Project

LTE-24E-S2-2 AC-DC Adapter for RTC-700C

2. Power Manufacturer

LI TONE ELECTRONICS CO.,LTD

3. Team Member

PM : Hero Chen ; EE : Changwen Zhou

4. Test Equipment

4.1. CPU Board : AAEON , RTC-700C , Rev.0.2

4.2. CPU : Intel Atom Z2760 1.80GHz(Clover Trail)

4.3. Memory : LPDDR2 / 2GB

4.4. Storage Disk Drive : 64GB Emmc

4.5. OS : Windows Embedded 8.1 Industry Pro Evaluation

4.6. BIOS:RTC-700C Rev 0.41(10/30/2013)

4.7. AC Adapter : LTE , Model : LTE24E-S2-2 , O/P : 12V/2A , 24Watt

5. AC Adapter Spec

AC Input : 100VAC~240VAC / 47Hz~63Hz

DC Output : 12Vdc Min Load : 0A ; Max Load : 2A / 24W

6. Test Item

Test Item	Test Condition / Specification		Sanction	
			Measured	Result
6.1. AC Input Current	I/P:115VAC	0.45A	0.42A	Passed
6.2. MAX Inrush Current	I/P:115VAC	A	-	N/A
	I/P:230VAC	A	-	N/A
6.3. Input Frequency & Voltage	I/P:90VAC/47HZ	■ON □ OFF	-	Passed
	I/P:90VAC/63HZ	■ON □ OFF	-	Passed
	I/P:264VAC/47HZ	■ON □ OFF	-	Passed
	I/P:264VAC/63HZ	■ON □ OFF	-	Passed
6.4. Switching Test	Switching Time: 0.5 Sec MIN Load / Full Load	@90VAC ■ON □ OFF	-	Passed
	Switching Time: 0.5 Sec MIN Load / Full Load	@115VAC ■ON □ OFF	-	Passed
	Switching Time: 0.5 Sec MIN Load / Full Load	@230VAC ■ON □ OFF	-	Passed
	Switching Time: 0.5 Sec MIN Load / Full Load	@264VAC ■ON □ OFF	-	Passed
6.5. Efficiency	I/P:90VAC FULL LOAD	@80%Min	80.546%	Passed
	I/P:115VAC FULL LOAD	@80%Min	82.483%	Passed
	I/P:230VAC FULL LOAD	@80%Min	84.408%	Passed
	I/P:264VAC FULL LOAD	@80%Min	83.215%	Passed
6.6. Line Regulation	I/P:90VAC~264VAC	<±1%	-0.2%	Passed
6.7. Load Regulation	I/P:115VAC O/P:MINLOAD~FULL LOAD	<±4%	2.308%	Passed
	I/P:230VAC O/P:MINLOAD~FULL LOAD	<±4%	2.475%	Passed
6.8. Over-Voltage Protection	I/P:230VAC O/P:MIN LOAD	V1 : 15.6V (MAX)	-	N/A
6.9. Over-Circuit Protection	O/P: 12V	A(MAX)	3.4A	Passed
6.10. Over-Load Protection	I/P:90VAC O/P:MIN LOAD	120~200%	168.5%	Passed
	I/P:115VAC O/P:MIN LOAD	120~200%	170.6%	Passed
	I/P:230VAC O/P:MIN LOAD	120~200%	171.6%	Passed
	I/P:264VAC O/P:MIN LOAD	120~200%	168.7%	Passed
6.11. Short Circuit Protect	I/P:115VAC O/P:MIN LOAD	12V&GND Short	-	Passed
	I/P:230VAC O/P:MIN LOAD	12V&GND Short	-	Passed
6.12. Line Voltage Surge	O/P: FULL LOAD	Surge voltage from 132VAC to 147VAC (0.5sec), back to 132VAC		Passed
	O/P: FULL LOAD	Surge voltage from 264VAC to 293VAC (0.5sec), back to 264VAC		Passed

6.13. Line Voltage Sag	O/P: FULL LOAD	Sag voltage from 108VAC to 80VAC (0.5sec), back to 108VAC	-	Passed
	O/P: FULL LOAD	Sag voltage from 198VAC to 161VAC (0.5sec), back to 198VDC	-	Passed
6.14. Ripple & Noise	I/P:115VAC O/P:FULL LOAD	$\leq 120\text{mv}$	93mv	Passed
	I/P:230VAC O/P:FULL LOAD	$\leq 120\text{mv}$	94mv	Passed
6.15. Setup Time	I/P:115VAC O/P:FULL LOAD	3S(MAX)	915ms	Passed
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	370.5ms	Passed
6.16. Hold up Time	I/P:115VAC O/P:FULL LOAD	10mS(MIN)	16.9ms	Passed
	I/P:230VAC O/P:FULL LOAD	8mS(MIN)	76.5ms	Passed
6.17. Rise Time	I/P:115VAC O/P:FULL LOAD	mS(MAX)	8.102ms	N/A
	I/P:230VAC O/P:FULL LOAD	mS(MAX)	7.841ms	N/A
6.18. Turn on Overshoot	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	Passed
	Turn on overshoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	Passed
6.19. Turn off Undershoot	Turn off undershoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	Passed
	Turn off undershoot shall not exceed 10% over nominal voltages@ 20 % LOAD		-	Passed
6.20. Remote ON/OFF	Simulate TTL signal to test this function		-	-
6.21. Power Good Signal	Shall go high level with a delay of100~500ms		-	-
6.22. Power On In Low Temperature	I/P:115VAC (°C) After 2HR Power On		-	-
6.23. Power On In High Temperature	I/P:115VAC (°C)After 2HR Power On		-	-
6.24. Power Consumption Test with AC Adapter	No Burn-in Test	I/P:100VAC 0.39A 23W	O/P: 12V/1.57A 18.84W	Passed
	Run Burn-in Test	I/P:100VAC 0.41A 23.8W	O/P: 12V/1.62A 19.44W	Passed